



List Price \$703.00 USD

Availability **Stock Item: This item is normally stocked in our distribution facility.****Technical Characteristics**

Depth	6.38 Inches
Height	17.50 Inches
Wire Size	#12 to #2 AWG(Al) or #14 to #2 AWG(Cu)
Width	9.00 Inches
Action	Single Throw
Ampere Rating	60A
Approvals	UL Listed
Catalog Reference Number	3100CT9801
Electrical Interlock	None
Enclosure Rating	NEMA 3R
Enclosure Material	Galvannealed Steel
Factory Installed Neutral	No
Enclosure Type	Rainproof and Sleet/Ice proof (Indoor/Outdoor)
Maximum Voltage Rating	600V
Terminal Type	Lugs
Disconnect Type	Fusible
Mounting Type	Surface
Type of Duty	Heavy Duty
Short Circuit Current Rating	10kA (Class H or K) - 200kA (Class R,J or L)
Number of Poles	3-Pole

**Shipping and Ordering**

Category	00009 - Safety Switch, Heavy Duty, 2 & 3 Pole, 30-200 Amp, Outdoor
Discount Schedule	DE1
Article Number	785901482185
Package Quantity	1
Weight	15.43 lbs.
Availability Code	Stock Item: This item is normally stocked in our distribution facility.
Returnability	Y

As standards, specifications, and designs change from time to time, please ask for confirmation of the information given in this document.

**Table 3.9: 600 Volts—Single Throw Fusible**

System	Amperes	NEMA 1 Indoor		NEMA 3R Rainproof (Bolt-on Hubs, page 3-11)		NEMA 4, 4X, 5A 304 Stainless Steel (for 316 stainless, see page 3-7) Dust tight, Watertight, Corrosion Resistant (Watertight Hubs, page 3-11)		NEMA 12K With Knockouts (Watertight Hubs, page 3-11)		NEMA 12, 3R# Without Knockouts (Watertight Hubs, page 3-11)		Horsepower Ratings*				dcv		
		Cat. No.	\$ Price	Cat. No.	\$ Price	Cat. No.	\$ Price	Cat. No.	\$ Price	Cat. No.	\$ Price	480 Vac		600 Vac				
												Std. (Using Fast Acting, One Time Fuses)	Max. (Using Dual Element, Time Delay Fuses)	Std. (Using Fast Acting, One Time Fuses)	Max. (Using Dual Element, Time Delay Fuses)	3Ø	3Ø	3Ø
<b>2-Wire (2 Blades and Fuseholders)—600 Vac, 600 Vdc</b>																		
	30																	
	60																	
	100																	
	200																	
	400	H265	4206.00	H265R	5424.00	H265DS	14961.00			H265AWK	5025.00							
	600	H266	6653.00	H266R	10686.00	H266DS	21399.00			H266AWK	7341.00							
800	H267	10365.00	H267R	16385.00					H267AWK	15276.00								
1200	H268	14570.00	H268R	17991.00					H268AWK	18044.00								
<b>3-Wire (3 Blades and Fuseholders)—600 Vac, 600 Vdc</b>																		
	30	H361	528.00	H361RB	899.00	2520.00		H361A	1014.00	H361AWK	956.00	5	15	7-1/2	20	5	15	
	30	H361-2Δ	617.00	H3612RBΔ	1049.00			H361-2AΔ	1035.00	H3612AWKΔ	977.00	5	15	7-1/2	20		30	
	60	H362	638.00	H362RB	1055.00		H362DS	2771.00		H362A	1047.00	H362AWK	984.00	15	30	15	50	15
	100	H363	1188.00	H363RB	1644.00		H363DS	5493.00		H363A	1626.00	H363AWK	1539.00	25	60	30	75	50
	200	H364	1707.00	H364RB	2259.00		H364DS	7685.00		H364A	2544.00	H364AWK	2400.00	50	125	60	150	40
	400	H365	4551.00	H365R	5532.00		H365DS	15321.00				H365AWK	5462.00	100	250	125	350	50
	600	H366	7649.00	H366R	10899.00		H366DS	21084.00				H366AWK	9203.00	150	400	200	500	50
	800	H367	13319.00	H367R	16500.00							H367AWK	16352.00	200	500	250	500	50
1200	H368	17507.00	H368R	20009.00							H368AWK	19706.00	200	500	250	500	50	
<b>4-Wire (3 Blades and Fuseholders, 1 Neutral)—600 Vac, 600 Vdc</b>																		
	30	H361N	617.00	H361NRB	986.00							5	15	7-1/2	20		15	
	60	H362N	710.00	H362NRB	1134.00							15	30	15	50		30	
	100	H363N	1278.00	H363NRB	1737.00							25	60	30	75		50	
	200	H364N	1869.00	H364NRB	2408.00		H364NDS	7871.00	H364NA	2715.00	H364NAWK	2558.00	50	125	60	150	40	50
	400	H365N	4898.00	H365NR	5765.00		H365NDS	15668.00				H365NAWK	5823.00	100	250	125	350	50
	600	H366N	8019.00	H366NR	11054.00		H366NDS	22122.00				H366NAWK	9600.00	150	400	200	500	50
	800	H367N	14043.00	H367NR	17205.00							H367NAWK	17253.00	200	500	250	500	50
	1200	H368N	18114.00	H368NR	20993.00							H368NAWK	20820.00	200	500	250	500	50
<b>4-Wire (4 Blades and Fuseholders)—600 Vac, 600 Vdc</b>																		
	30	H461	914.00				H461DS	2937.00			H461AWK	1115.00	7-1/2	20	10	25	5	15
	60	H462	1065.00				H462DS	3069.00			H462AWK	1257.00	15	40	20	50	10	30
	100	H463	1778.00				H463DS	8345.00			H463AWK	1932.00	25	50	30	75	20	30
	200	H464	2957.00				H464DS	12596.00			H464AWK	3222.00	50		50		40	50
	400	H465	6210.00								H465AWK	6807.00	100	250	125	350	50	50
	600	H466	10104.00										150	400	200	500	50	50
<b>6-Wire (6 Blades and Fuseholders)—600 Vac</b>																		
	100						H663DS	25964.00			H663AWK	5112.00	25	60	30	75		
	200						H664DS	35393.00			H664AWK	12222.00	For applications requiring motor disconnect capability, use electrical interlock. Refer to page 3-11.					

- ▲ Complete rating is NEMA 3, 3R, 4, 4X, 5 and 12.
- Also suitable for NEMA 3R application by removing drain screw from bottom endwall.
- ◆ Refer to page 7-35 for additional motor application data. The starting current of motors of more than standard horsepower may require the use of fuses with appropriate time delay characteristics.
- ★ For corner grounded delta systems only and with neutral assembly installed. Use switching poles for ungrounded conductors.
- ☆ On 3P devices, use two outside poles for switching dc.
- Δ 60 A switch with 30 A fuse spacing and clips. Must use 60 A enclosure accessories including electrical interlocks.
- Suitable for NEMA 5 applications with drain screw installed.
- ◇ Not suitable for use as service equipment.

**Class H Fuse Provisions:**

Fusible Square D 30 through 600 A heavy duty safety switches accept Class H fuses as standard. With Class H fuses installed, the switch is UL Listed for use on systems with up to 10 kA available fault current.

**Class R Fuse Provisions:**

Fusible Square D 30–600 A heavy duty safety switches will accept Class R fuses as standard. A field-installed rejection kit is available which, when installed, rejects all but Class R fuses. With the installation of the rejection kit and Class R fuses, the switch is UL Listed for use on systems with up to 200 kA available fault current. See Class R fuse kits on page 3-11.


**Class J Fuse Provisions:**

Provisions for installing Class J fuses are included in 30 through 400 A 600 Volt, and 100 through 400 A 240 Volt, fusible heavy duty safety switches. Conversion to Class J fuse spacing requires relocating the load side fuse base assembly from the standard Class H fuse location to an alternate position as marked in the enclosure. With Class J fuses installed, the switch is UL Listed for use on systems with up to 200 kA available fault current. Switches rated 600 A, 240 or 600 Volt, require the addition of an adapter kit, H600J at \$456. One kit per 3P switch.

**Class L Fuse Provisions:**

Fusible 800 A and 1200 A safety switches use Class L bolt-in fuses and are rated for use on systems with up to 200 kA at 600 Vac maximum. 1200 A switches accept class L fuses from 601–1200 A, 800 A switches accept class L fuses from 601–800 A.

Accessories: .....pages 3-11 through 3-13  
Dimensions: NEMA 1 and 3R .....page 3-14  
Dimensions: NEMA 4, 4X and 5 .....page 3-15



Class R Fuse